


#### 92 SERIES SPRING LOADED STAINLESS STEEL NIPPLE UNION

#### Description


The 92 series are the ATEX and IECEx approved spring loaded stainless steel nipple union assemblies that can be used with any approved equipment or transmitter that offers at least the same level of protection as detailed at the bottom of this page. This allows the entire assembly to be ATEX and IECEx approved. The assembly has a 1/2" NPT thread at the probe end and a 1/2" NPT or M20 thread at the lead end (thread for flame lock). The probe end of the nipple union is threaded to accommodate an optional protection of the probe such as a thermowell.

The 92 series comes with an option for a customized stainless steel nameplate that can be attached on the union. We can also provide these assemblies with a sensor from any manufacturer of your choice. See below for ordering information.




#### **Certification System**






#### Description

The 93 series are a variation of the 92 series where these are the ATEX and IECEx approved spring loaded stainless steel nipple assemblies. This assembly can also be used with any approved equipment or transmitter that offers at least the same level of protection as detailed at the bottom of this page. This thus allows the entire assembly to be ATEX and IECEx approved The assembly has a 1/2" NPT thread at the probe end and a 1/2" NPT or M20 thread at the lead end. The probe end of the nipple union is threaded to accommodate an optional protection of the probe such as a thermowell. See below for ordering information.



#### **Certification System**








# EXPLOSION PROOF TEMPERATURE ASSEMBLY


#### 98 SERIES SPRING LOADED STAINLESS STEEL NIPPLE UNION


#### Description

The 98 series are ATEX and IECEx approved temperature assemblies. These temperature assemblies encompasses our 8080KN Battery Operated Digital Temperature Indicator, 8080PR Indicating Temperature Temperature switch with Dual Relays, 8080PN Indicating Transmitter Transmitter and our 8080HT Indicating Temperature Transmitter with Hart®. See below for ordering information.



#### **Certification System**





#### **DIGITAL TEMPERATURE INDICATORS**

#### MODEL 8080KN BATTERY OPERATED DIGITAL TEMPERATURE INDICATOR

Model 8080KN is a Battery Operated Digital Temperature Indicator which accepts an input from a standard Type J or K Thermocouple or RTD and provides local indication of temperature in degree F or C. The 8080KN becomes a universal instrument since only one instrument will indicate the entire useful range of the thermocouple or RTD (-100 to +1400 °C).

#### **Functional Specifications**

Sensor

Thermocouple Type J / K or RTD Pt100

Indication Accuracy

0.5 Degree C

Display Height

12.5mm (1/2") high

**Display Units** 

°C or °F, switch selectable

**Battery Life** 

Approx. 24 Months

Calibration

Single point calibration for enhanced accuracy

#### MODEL 8080PR TEMPERATURE INDICATING SWITCH WITH DUAL RELAYS

#### Description

Model 8080PR allows 2 independent alarms to be assigned over the temperature range of the sensor. The unit will accept an input from a Pt100 RTD or Type J or K thermocouple and provide an indication on a bright 4 digit LED. The unit serves a dual purpose since in addition to local indication of temperature, which is switch selectable to read °C or °F, it also serves as an accurate and repeatable temperature switch.

#### **Functional Specifications**

Indication Accuracy

0.1% of Calibrated range +/- 1 digit

Set Point Adjustment

10~100% of full scale, user selectable

Reset

Automatically when the input falls below the alarm set point by approximately ±0.5% of full scale

#### **Alarm Set Point Accuracy**

±0.5% of full scale.

**Alarm Status Indication** 

LED on front panel

**Display Height** 

12.5mm (1/2") high

**Alarm Output** 

2 sets SPDT, 1 from C, rated 10A @ 250V AC, 50/60Hz

**Stability Over Time** 

0.1% of calibrated range ± 1 digit over 6 months

**Over Range Indication** 

Flashing of display

Response Time

Typically 75ms

Supply Voltage 18~28V DC

### **MODEL 8080PN TEMPERATURE TRANSMITTER**

#### **Description**

Model 8080PN is a two wire indicating transmitter which coverts input from a Type J/K Thermocouple or Pt100 sensor into a load independent 4-20mA process signal. A 4 digit bright red LED allows for local indication of Temperature, which is switch selectable to read °C or °F.

#### **LED Meter**

Model 8080PN has 4 digit bright red LED and may be configured to read temperature in either degrees C or F. The zero and span setting for 4 to 20mA signal as well as the units of display can be set either using the membrane switches on the front panel, eliminating potentiometric adjustments.

# **Functional Specifications**

Type J/K Thermocouple or Pt100 RTD

**Indication Accuracy** 0.1% of Calibrated range ± 1 digit

**Lead Compensation Error** 

 $<\pm0.05/10\Omega$  lead resistance

**Stability Over Time** 

0.1% of calibrated range ±1 digit over 6 months

Temperature Stability

±0.01% per Degree C Adjustable Span

Over the entire range of sensor (Minimum Span=20 °C) (about 30 °F)

**Burnout Protection** 

Upscale

Supply Voltage

18~28V DC

Supply and Load Effect

<0.03% of span for full change

## **MODEL 8080HT TEMPERATURE TRANSMITTER WITH HART®**

# Description

Model 8080HT is a digital, PC/Hand-Held programmable, isolated 2-wire transmitter with HART® protocol. The unit converts 8 types of thermocouples; 8 types of RTDs, configured as 2, 3 and 4 wires; potentiometer, resistor and millivolt inputs into process current loop.

Exceptional digital accuracy of typical ±0.1 °C is provided for all the sensors regardless of the calibrated span. Extremely accurate cold-junction temperature measurement provides precise compensation throughout the entire ambient range. The unit also accurately measures and compensates the RTD sensor leads in the 3-wire connection.

The transmitter is fully configurable by connecting to a PC or a Hand-Held programmer. The configuration parameters are stored in a non volatile memory. Detection of sensor breakage or disconnection of input leads, forces the output to a pre-defined up/down scale value. The unit continuously monitors the sensor and automatically returns to normal operation mode when the sensor is recovered.

Continue on Page 3.

# **Functional Specifications**

Output

4~20mA with HART® protocol ( 2 wire )

Supply Voltage

10.5 to 45 VDC (with backlight LCD)

Input

RTD. TC. Ohm. mV Accuracy (Pt100)

< 0.2K or 0.08%

**Cold Junction Compensation** 

Internal

Galvanic Isolation

2 KVAC (In/Out)

**Influence of Ambient Temperature** 

Negligible

Load Influence Negligible

Resolution

0.3 uA

### Input

	Туре	Measurement Ranges	Min. meas. Ranges	Maximum Measured Error
	Pt100	-200 ℃ to 850 ℃ (-328 ℉ to 1562 ℉)	10K	0.2K or 0.08%
	Pt500	-200 ℃ to 850 ℃ (-328 ℉ to 1562 ℉)	10K	0.5K or 0.20%
	Pt1000	-200 ℃ to 850 ℃ (-328 ℉ to 1562 ℉)	10K	0.3K or 0.12%
Resistance	Cu50	-50 °C to 150 °C (-58 °F to 302 °F)	10K	0.2K or 0.08%
Thermocouple (RTD)	Cu100	-50 ℃ to 150 ℃ (-58 ℉ to 302 ℉)	10K	0.3K or 0.12%
	Ni100	-60 °C to 180 °C (-76 °F to 356 °F)	10K	0.2K or 0.08%
	Ni500	-60 ℃ to 180 ℃ (-76 ℉ to 356 ℉)	10K	0.5K or 0.20%
	Ni1000	-60 °C to 180 °C (-76 °F to 356 °F)	10K	0.3K or 0.12%
ResistanceTransmitter		0 to 400 Ω	10 Ω	± 0.1Ω or 0.08%
	Resistance (Ω)	0 to 2000 Ω	20 Ω	± 1.5Ω or 0.12%
		0 to 10000 Ω	100 Ω	± 7.5Ω or 0.20%
	B (PtRh30-PtRh6)	0 to 1820 ℃ (32 to 3308 ℉)	500K	
	E (NiCr-CuNi)	-270 to 1000 ℃ (-454 to 1832 ℉)	50K	typ. 0.5K or 0.08%
	J (Fe-CuNi)	-210 to 1200 ℃ (-346 to 2192 ℉)	50K	typ. 0.5K or 0.08%
Thormocounic (TC)	K (NiCr-Ni)	-270 to 1372 ℃ (-454 to 2501 ℉)	50K	typ. 0.5K or 0.08%
Thermocouple (TC)	N (NiCrSi-NiSi)	-270 to 1300 ℃ (-454 to 2372 ℉)	50K	typ. 1.0K or 0.08%
	R (PtRh13-Pt)	-50 to 1768 ℃ (-58 to 3214.4 ℉)	500K	typ. 2.0K or 0.08%
	S (PtRh10-Pt)	-50 to 1768 ℃ (-58 to 3214.4 ℉)	500K	typ. 2.0K or 0.08%
	T(Cu-CuNi)	-270 to 400 ℃ (-454 to 752 ℉)	50K	typ. 0.5K or 0.08%
VoltageTransmitters (mV)		-10 to 75 mV	5 mV	± 20 μV or 0.08%
	Millivolt	-100 to 100 mV	5 mV	± 20 μV or 0.08%
	transmitter(mV)	-100 to 500 mV	6 mV	± 30 μV or 0.08%
		-100 to 2000 mV	20 mV	± 50 μV or 0.08%

## **Output**

Output Signal	4 to 20 mA + Hart®	4 to 20 mA + Hart®	
Signal On Alarm	Underranging	Linear drop to 3.8 mA	
	Overranging	Linear rise to 20.8 mA	
	Sensor break; sensor open-circuit	<3.8 mA	
Load	Max. (V <sub>power supply</sub> - 7.5 V) / 0.0208A	Max. (V <sub>power supply</sub> - 7.5 V) / 0.0208A (without display)	
	Max. (V <sub>power supply</sub> - 10.5 V) / 0.0208	Max. (V <sub>power supply</sub> - 10.5 V) / 0.0208A (with display)	
Linearization/Transmission	Tomporatura linear, registance line	Temperature linear, resistance linear, voltage linear	
Behavior	remperature intear, resistance line		
Galvanic Isolation	U = 2 KV AC (input/output)	U = 2 KV AC (input/output)	

### **Power Supply**

Supply Voltage (polarity protected)	$U_b = 10.5 \text{ to } 45 \text{ VDC}$
-------------------------------------	-----------------------------------------

#### **Performance Characteristic**

Response Time	1s	
Reference Operating	Calibration Temperature : 23 °C (73.4 °F) ± 5K	
Conditions		
Long Term Stability	≤ 0.05% / year	
Switch On Delay	≤ 5s	
Self Stability Configuration	0 to 2%	
Filter Configuration	0 to 160 μA	
Resolution	0.3 μA	

# **Environment Condition**

Ambient Temperature	-40 to 85°C (-40°F to 195°F) Without display
Limits	-20 to 70 °C (-4 °F to 158 °F) With display
Storage Temperature	-40 to 100 °C (-40 °F to 212 °F)
Condensation	100%
Electromagnetic	Interference immunity and interference emission according
Compatibility (EMC)	to GB/T17626.2-1998), compliance with IEC 61000-4-3:1995




# EXPLOSION PROOF TEMPERATURE ASSEMBLY

#### 99 SERIES TEMPERATURE ASSEMBLY

#### Description

The 99 series ATEX and IECEx approved temperature assemblies incorporate a Thermocouple Head and a head mounted (hockey puck) temperature transmitter or a 6 post ceramic block. The sensor can be from any manufacturer and may include any thermowell (flanged or threaded). The nipple union assembly is then fitted to an IME Model 1080 Thermocouple Head (Aluminum or SS316). Any model head mounted (hockey puck) temperature transmitter that has less than 3 watts power dissipation or a 6 post terminal block is mounted in the Thermocouple Head to complete the approved temperature assembly. See below for ordering information.




### IME TEMPERATURE TRANSMITTER DETAILS

### **HEAD MOUNTED TRANSMITTER**

8070HN

- 2 wire, 4 to 20mA analog output
- High accuracy in total ambient temperature range
- An internal temperature sensor for active temperature compensation (For T/C)
- 3 year warranty






INPUT	TYPE
Platinum Resistance Sensors	Pt 100, Cu 50, Cu 100
Resistance Transmitter	0 to 400 Ω
Votage Transmitter (mV)	-10 to 75mV
Thermocouple Types	B,E,J,K,N,R,S and T
OUTPUT	
Output Signal	4 to 20 mA
Under Range	Linear Drop to 3.8mA
Over Range	Linear Rise to 20.8mA
Sensor Breakage	< 3.8mA
Load	Max. (V <sub>power supply</sub> - 7.5 V) / 0.0208A
POWER SUPPLY	
Supply Voltage	7.5 to 45 VDC, Polarity Protected
SPECIFICATION	
Response time	1s
Reference Operation Conditions	Calibration temperature: 23 °C (75 °F)
Long Term Stability	≤0.05% / Year
Infuence of ambient Temperature	Negligible
Load Influence	Negligible
Power Supply Influence	Negligible
Ambient Temperature Limits	-40 to 85 ℃

## **HEAD MOUNTED TRANSMITTER WITH HART®**

8070HH

- Universal settings with HART ® protocol for various input signals
- 2 wire, 4 to 20mA analog output + Hart ®
- High accuracy over total ambient temperature range
- Galvanic isolation
- An internal temperature sensor for active temperature compensation (For T/C)
- Wide voltage supply range
- 3 year warranty





INPUT	TYPE
Platinum Resistance Sensors	Pt100, Pt500, Pt1000, Cu50, Cu100,
	Ni100, Ni500, Ni1000
Resistance Transmitter Range/ Min Range	0 to 400 Ω / 10 Ω
	0 to 2000 Ω / 20 Ω
	0 to 10000 Ω / 100 Ω
Thermocouple Types	B,E,J,K,N,R,S and T
Voltage Transmitters (mV) / Min Range	-10 to 75mV / 5mV
	-100 to 100mV / 5mV
	-100 to 500mV / 6mV
	-100 to 2000mV / 20mV
OUTPUT	
Output Signal	4 to 20 mA + Hart®
Under Range	Linear Drop to 3.8mA
Over Range	Linear Rise to 20.8mA
Load	Max. (V <sub>power supply</sub> - 7.5 V) / 0.0208A
Galvanic Isolation	U=2KV AC (input/ output)
POWER SUPPLY	
Supply Voltage	7.5 to 45 VDC/ Polarity Protected
SPECIFICATION	
Programmable	Easy programming with USB
Response Time	1s
Reference Operating Conditions	Calibration Temperature:23 °C ± 5K
Long Term Stability	≤ 0.05% / year
Switch On Delay	≤ 5s
Self Stability Configuration	0 to 2%
Filter Configuration	0 to 160 μA
Input Current Required	≤3.8mA
Current Limit	≤20.8mA
Ambient Temperature Limits	-40 to 85 ℃